

KENWOOD

Listen to the Future



TK-7100(H)/8100(H)

Compact Synthesized FM Mobile Radios

FleetSync[®]
by KENWOOD

Compact yet offering many powerful features, Kenwood's TK-7100(H)/8100(H) mobiles are designed to play the leading role in your communications. These radios are also built tough enough to withstand all the rigors of today's demanding applications.

ALPHANUMERIC LCD DISPLAY

The luminous LCD found on the TK-7100(H)/8100(H) offers user-friendly operation thanks to its 13-segment, 8-digit alpha-numeric display with multiple capabilities.



64 CHANNELS

Providing you with more versatility and convenience, the memory allocation of the TK-7100(H)/8100(H) allows programming of up to 8 groups within 64 channels.

SCAN FUNCTIONS

Priority Scan and Group Scan (single/multi) can be set; add and delete channel(s) function can also be performed.

TOUGH, COMPACT CONSTRUCTION

Built to take rough treatment in stride, the TK-7100(H)/8100(H) meets ten stringent MIL-STD 810 C/D/E/F standards. The "bathtub"



construction of the chassis assures excellent heat dissipation characteristics, and installation is simplified thanks to the compact external dimensions — 160mm (W) x 43mm (H) x 107mm (D). 137mm (D) for (H) version.



* Picture shown standard version.

HIGH-QUALITY SPEAKER

The large-diameter oval (58mm x 35mm) speaker mounted in the front panel assures excellent clarity.

DTMF / MSK PTT ID

The TK-7100(H)/8100(H) features two PTT ID formats — DTMF (max. 16-digit DTMF code) and MSK (FleetSync[®] format ID). PTT ID is a digital ANI (Automatic Number Identifier) that can be sent on each PTT, allowing clear identification of the person using the transceiver.

VERSATILE DTMF MODES

The TK-7100(H)/8100(H) can be set for the following DTMF encode and decode modes:

- **Code Squelch:** DTMF code squelch provides a 3- to 10-digit ID for DTMF paging operations.
- **Selective Call:** DTMF selective calling is a signalling function comprised of DTMF codes (ID code + Intermediate code + Status code) that allows reception even if the radio is left unattended. SQ opens when the set ID and intermediate code matches the maximum display of the 5-digit numeric status code.

- **Number display*:** When the DTMF code is received — such as the PTT ID number — it is displayed on the LCD for instant recognition.

* Does not operate while Code Squelch or Selective Call is activated.

OPERATOR SELECTABLE TONE

Users can freely change the 16 QT/DQT signalling tones that were set with the FPU; each signalling tone can also have an 8-digit name.

OTHER FEATURES

- Built-in QT/DQT Signalling
- SmarTrunk II™ OMNI capability (requires SmarTrunk board*)
- Data Ready (KDS-100, KGP-2A/2B, and 8 Programmable Function Port)
- Encryption Control Capability
- PC**/Self Programming
- AVL capability (with KGP-2A/2B)
- Backlit keys for all buttons
- Ignition sense input
- 4-Pro-grammable Keys
- Busy Channel Lockout
- Embedded Message
- Security features including Radio stun, Radio password, Data password, Embedded message, and Kenwood ESN
- Channel direct
- Time out Timer (TOT)
- Wide/narrow selection per channel

* SmarTrunk board is available from SmarTrunk Systems, Inc.

** Compatible with Windows 98/ME/2000/XP, English or Spanish version.



Options

■ **KMC-30**
Microphone



■ **KMC-32**
16-key Keypad
Microphone



■ **KMC-9C**
Desktop Microphone



■ **KES-3**
External Speaker



■ **KLF-2**
Line Filter



■ **KPS-10A**
Regulated DC
Power Supply



■ **KMB-10**
Key Lock Adapter



■ **KMB-19**
Installation Kit



■ **KGP-2A**
GPS Receiver Modem
(requires KCT-39 option)



■ **KGP-2B**
GPS Controller Modem
(requires KCT-39 option)



■ **KDS-100**
Mobile Data Terminal
(requires KCT-39 option)



■ **KCT-18**
Ignition Sense Cable
(requires KCT-39 option)



■ **KCT-36**
3m Extension Cable
(for KCT-39)



■ **KCT-39**
Connection Cable



All accessories and options may not be available in all markets. Contact an authorized Kenwood dealer for details and complete list of all accessories and options.

Specifications

	TK-7100(H)	TK-8100(H)	TK-7100(H)	TK-8100(H)
GENERAL				
Frequency Range			RECEIVER (Measurements made per EIA/TIA-603)	
Type 1	146-174 MHz	440-480 MHz	Sensitivity (Wide / Narrow)	
Type 2	136-162 MHz	400-430 MHz	0.28µV / 0.35µV (12dB SINAD)	
Channels / Groups	64 CH / 8 GRP (Up to 64 channels can be allocated into 8 groups)		Selectivity (Wide / Narrow)	
Channel Spacing (Wide / Narrow)	25 kHz / 12.5 kHz		75 dB / 65 dB	
PLL Channel Stepping	2.5 kHz, 5 kHz, 6.25 kHz, 7.5 kHz		Intermodulation Distortion (Wide / Narrow)	
Operating Voltage	13.6 V, DC ±15%		70 dB / 60 dB	
Current drain			Spurious Response	
Standby	0.4 A		75 dB	
Receive	1.0 A		Audio Output (4Ω, 5% Distortion)	
Transmit* / (H)	8.0 A / 14.0 A		4.0 W	
Operating Temperature Range	-30°C ~ +60°C		TRANSMITTER (Measurements made per EIA/TIA-603)	
Frequency Stability (-30°C ~ +60°C)	±2.5 ppm		RF Power Output	
Dimensions			Standard Version (High / Low)	
(W x H x D, without projections)	160 mm x 43 mm x 107 mm (137 mm for H)		25W / 5W	
Weight (Body only, approximate)	1.0 kg / 1.18kg for H		RF Power Output	
Antenna Impedance	50 Ω		High Power Version (High / Low)	
Channel Frequency Spread			50W / 25W	
Type 1	28 MHz	40 MHz	Spurious & Harmonics	
Type 2	26 MHz	30 MHz	70 dB	
			Modulation (Wide / Narrow)	
			16K0F3E / 11K0F3E	
			FM Noise (Wide / Narrow)	
			45 dB / 40 dB	
			Audio Distortion	
			Less than 3%	
			Microphone Impedance	
			600Ω	

Kenwood reserves the right to change specifications and features without prior notice.
SmarTrunk II™ is a trademark of SmarTrunk Systems, Inc.
Fleetsync® is a registered trademark of Kenwood Corporation.

Applicable MIL-STD

Standard	MIL 810C Methods/Procedures	MIL 810D Methods/Procedures	MIL 810E Methods/Procedures	MIL 810F Methods/Procedures
Low Pressure	500.1 / Procedure I	500.2 / Procedure I, II	500.3 / Procedure I, II	500.4 / Procedure I, II
High Temperature	501.1 / Procedure I, II	501.2 / Procedure I, II	501.3 / Procedure I, II	501.4 / Procedure I, II
Low Temperature	502.1 / Procedure I	502.2 / Procedure I, II	502.3 / Procedure I, II	502.4 / Procedure I, II
Temperature Shock	503.1 / Procedure I	503.2 / Procedure I	503.3 / Procedure I	503.4 / Procedure I, II
Solar Radiation	505.1 / Procedure I	505.2 / Procedure I	505.3 / Procedure I	505.4 / Procedure I
Humidity	507.1 / Procedure I, II	507.2 / Procedure II, III	507.3 / Procedure II, III	507.4
Salt Fog	509.1 / Procedure I	509.2 / Procedure I	509.3 / Procedure I	509.4
Sand & Dust	510.1 / Procedure I	510.2 / Procedure I	510.3 / Procedure I	510.4 / Procedure I, III
Vibration	514.2 / Procedure VIII, X	514.3 / Procedure I Cat. 8	514.4 / Procedure I Cat. 8	514.5 / Procedure I Cat. 20
Shock	516.2 / Procedure I, II, III, V	516.3 / Procedure I, IV, V	516.4 / Procedure I, IV, V	516.5 / Procedure I, IV, V

Listen to the Future

Kenwood has always connected with people through sound. Now we want to expand the world of sound in ways that only Kenwood can, listening to our customers and to the pulse of the coming age as we head toward a future of shared discovery, inspiration and enjoyment.

Kenwood Corporation

2967-3, Ishikawa-machi, Hachioji, Tokyo 192-8525, Japan

Kenwood Electronics Singapore Pte. Ltd.

1 Ang Mo Kio Street 63 Singapore 569110

